



### MODEL OVERVIEW

<b>SPEED</b>	3000RPM
<b>POWER</b>	7kW / 8kVA
<b>FUEL TYPE</b>	PETROL
<b>FUEL CAPACITY</b>	6.1L
<b>CONTINUOUS OUTPUT</b>	8kVA

### ADDITIONAL INFO

<b>OUTLETS</b>	1 x 10AMP 415V, 2 x 15AMP 240V SWITCHED WITH THERMAL OVERLOAD
<b>FRAME</b>	LARGE ROLL FRAME
<b>NOISE RATING</b>	72 dBA @ 7M

### TECHNICAL

<b>MODEL</b>	GH7000/3
<b>TYPE</b>	PORTABLE
<b>FREQUENCY</b>	50Hz
<b>PHASE/VOLTAGE</b>	3/415

### Honda Powered Heavy Duty Industrial Generators

This range from Genelite proudly features the world-renowned Honda GX series of engines, that deliver reliable, high-performance power for homes, businesses and job sites.

Featuring a durable open-frame design and genuine Honda Engine, these generators are designed to provide maximum power output, making them perfect for heavy-duty applications. They deliver consistent and stable power to keep your tools, equipment, and appliances running smoothly. With unmatched durability and performance, these generators are built to handle even the toughest jobs.

Materials and specifications are subject to change. Specification sheets are current as of 30/6/2025.

### FEATURES

HONDA PETROL ENGINE
HEAVY DUTY ROLL FRAME
RECOIL START
3 YEAR LIMITED ENGINE WARRANTY

### ENGINE

<b>MANUFACTURER</b>	HONDA
<b>ENGINE MODEL</b>	GX390
<b>TYPE &amp; CYLINDER</b>	O.H.V. SINGLE CYLINDER
<b>STARTING</b>	RECOIL
<b>RUN TIME</b>	2.6HR @ 100%, 3.8HR @ 60% LOAD
<b>CUBIC CAPACITY</b>	389 CM <sup>3</sup>
<b>HP 3000 RPM CONT</b>	8 HP
<b>OIL CAPACITY</b>	1.1 L

### ALTERNATOR

<b>TYPE</b>	AC SYNCHRONOUS BRUSHLESS
<b>HARMONIC DISTORTION</b>	LESS THAN 5%
<b>INSULATION CLASS</b>	CLASS H

### DIMENSIONS

<b>LENGTH</b>	77 CM
<b>WIDTH</b>	49 CM
<b>HEIGHT</b>	57 CM
<b>WEIGHT (DRY)</b>	80 KG

### OPTIONS

HIRE SPEC: 2 x IP66 RATED OUTLETS, CIRCUIT BREAK and RCD PROTECTION
2 OR 4 WHEEL KIT
EXTRA LARGE ROLL FRAME
LONG RANGE TANK
ELECTRIC START, FULL AMF, REMOTE START

The warranty does not cover damage caused by misuse, neglect, accident, improper installation, unauthorised repairs or modifications, normal wear and tear, or use of non-approved fuels or oils. Consumable parts such as filters, fuses, and cosmetic wear are not covered.

The generator must be serviced at regular intervals as specified in the user manual. Proof of purchase and service records may be required. As the Australian distributor, Genelite reserves the right to repair or replace defective parts at its discretion.