



MODEL OVERVIEW	
<b>SPEED</b>	3000RPM
<b>POWER</b>	7kW / 8kVA
<b>FUEL TYPE</b>	PETROL
<b>FUEL CAPACITY</b>	6.1L
<b>CONTINUOUS OUTPUT</b>	8kVA

ADDITIONAL INFO	
<b>OUTLETS</b>	1 x 10AMP and 1 x 15AMP 240V SWITCHED WITH THERMAL OVERLOAD
<b>FRAME</b>	EXTRA LARGE ROLL FRAME
<b>NOISE RATING</b>	72 dBA @ 7M

TECHNICAL	
<b>MODEL</b>	GH7000E
<b>TYPE</b>	PORTABLE
<b>FREQUENCY</b>	50Hz
<b>PHASE/VOLTAGE</b>	1/240

### Honda Powered Heavy Duty Industrial Generators

This range from Genelite proudly features the world-renowned Honda GX series of engines, that deliver reliable, high-performance power for homes, businesses and job sites.

Featuring a durable open-frame design and genuine Honda Engine, these generators are designed to provide maximum power output, making them perfect for heavy-duty applications. They deliver consistent and stable power to keep your tools, equipment, and appliances running smoothly. With unmatched durability and performance, these generators are built to handle even the toughest jobs.

Materials and specifications are subject to change. Specification sheets are current as of 30/6/2025.

FEATURES	
HONDA PETROL ENGINE	
HEAVY DUTY ROLL FRAME	
ELECTRIC START	
3 YEAR LIMITED ENGINE WARRANTY	
AUTOMATIC VOLTAGE REGULATOR (AVR)	

ENGINE	
<b>MANUFACTURER</b>	HONDA
<b>ENGINE MODEL</b>	GX390E
<b>TYPE &amp; CYLINDER</b>	O.H.V. SINGLE CYLINDER
<b>STARTING</b>	ELECTRIC START
<b>RUN TIME</b>	2.6HR @ 100%, 3.8HR @ 60% LOAD
<b>CUBIC CAPACITY</b>	389 CM <sup>3</sup>
<b>HP 3000 RPM CONT</b>	8 HP
<b>OIL CAPACITY</b>	1.1 L

ALTERNATOR	
<b>TYPE</b>	AC SYNCHRONOUS BRUSHLESS
<b>HARMONIC DISTORTION</b>	LESS THAN 5%
<b>INSULATION CLASS</b>	CLASS H

DIMENSIONS	
<b>LENGTH</b>	77 CM
<b>WIDTH</b>	49 CM
<b>HEIGHT</b>	57 CM
<b>WEIGHT (DRY)</b>	80 KG

OPTIONS	
2 OR 4 WHEEL KIT	
LONG RANGE TANK (15L CAPACITY)	

The warranty does not cover damage caused by misuse, neglect, accident, improper installation, unauthorised repairs or modifications, normal wear and tear, or use of non-approved fuels or oils. Consumable parts such as filters, fuses, and cosmetic wear are not covered.

The generator must be serviced at regular intervals as specified in the user manual. Proof of purchase and service records may be required. As the Australian distributor, Genelite reserves the right to repair or replace defective parts at its discretion.