

P2000I

Compact & Lightweight



The right power for sensitive voltage surges.

Single phase power

Power LTP	kW	2.00
Power COP	kW	1.60
Voltage	V	230
Frequency	Hz	50
Power factor	cos ϕ	1

Ratings definition (According to standard ISO8528 1:2005)

COP - Continuous Power: It is defined as being the maximum power which a generating set is capable of delivering continuously for an unlimited number of hours, with the maintenance intervals and procedures being carried out as prescribed by the manufacturers.

LTP - Limited-Time running Power: It is defined as the maximum power available, under the agreed operating conditions, for which the generating set is capable of delivering for up to 500 h of operation per year (whose no more than 300 for continuative use) with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. No overload capability is available.

Engine

Engine manufacturer		Yamaha
Type		MZ80
Displacement	cm ³	79
Cylinder		1
Fuel		Petrol
Aspiration		Natural
Cooling System		Air
Starting system		Recoil

Consumption

Consumption at 75% of load	l/h	0.79
Tank capacity	l	4.2
Running time at 75% COP	h	5.3

Noise level

Acoustic power LWA	dB(A)	91
Acoustic pressure at 7m	dB(A)	59

Dimensions and weight

Length	(L) mm	498
Width	(W) mm	289
Height	(H) mm	461
Weight (dry)	Kg	22

Control Panel

Manual Start and Stop		•
Protection Control panel	IP	54
Parallel kit receptacles		•
Integrated radio disturbance filter		•
Battery charger (12V 8A)		•
Sockets	1 SCHUKO	230V 16A



Protection

Low oil level (oil guard)		•
Short circuit		•
Overload		•
Overspeed shutdown		•
Overtemperature		•
Decline or loss of phase frequency or voltage		•

• : Standard

- : Standard

The information is aligned with the Data file at the time of download. Printed on 04/03/2019 (ID 2927)

©2019 | PR INDUSTRIAL s.r.l. | All rights reserved | Image shown may not reflect actual package. Specifications subject to change without notice

