



MODEL OVERVIEW	
<b>SPEED</b>	3000RPM
<b>POWER</b>	5.6kW / 7kVA
<b>FUEL TYPE</b>	PETROL
<b>FUEL CAPACITY</b>	6.1 L

ADDITIONAL INFO	
<b>OUTLETS</b>	1 x 10AMP, 1 x 15 AMP SWITCHED WITH THERMAL OVERLOAD
<b>LEADS</b>	5 M LEADS WITH ELECTRODE HOLDER AND EARTH CLAMP
<b>FRAME</b>	LARGE ROLL FRAME
<b>NOISE RATING</b>	72 dBA @ 7 M

TECHNICAL	
<b>MODEL</b>	GHW200/7
<b>TYPE</b>	PORTABLE
<b>FREQUENCY</b>	50Hz
<b>PHASE/VOLTAGE</b>	1/240
<b>WELDER DUTY CYCLE</b>	200 AMP AC @ 35% 180 AMP AC @ 60%
<b>STRIKE VOLTAGE</b>	75V

### Honda Powered Generator Welder

The Honda Generator Welder combines dependable generator power with robust welding capability in one rugged, portable package. Powered by the legendary Honda GX390 engine, it delivers up to 7.0 kVA of generator output and 200 Amps of welding power, making it ideal for worksites, farms and remote applications. Built with a heavy-duty roll frame and designed for reliability, these units run power tools, lights and equipment, while also handling demanding welding tasks with ease.

Materials and specifications are subject to change. Specification sheets are current as of 30/6/2025.

FEATURES
200 AMP AC WELDER
HONDA PETROL ENGINE
RECOIL START
3 YEAR LIMITED ENGINE WARRANTY

ENGINE	
<b>MANUFACTURER</b>	HONDA
<b>ENGINE MODEL</b>	GX390
<b>STARTING</b>	RECOIL START
<b>RUN TIME</b>	2.6 HR @ 100%, 3.8 HR @ 60%
<b>CUBIC CAPACITY</b>	389 CM <sup>3</sup>
<b>HP 3000 RPM CONT</b>	8 HP
<b>OIL CAPACITY</b>	1.1 L

ALTERNATOR	
<b>TYPE</b>	AC SYNCHRONOUS BRUSHLESS
<b>HARMONIC DISTORTION</b>	LESS THAN 5%
<b>INSULATION CLASS</b>	CLASS H

DIMENSIONS	
<b>LENGTH / WIDTH / HEIGHT</b>	87 CM / 60 CM / 60 CM
<b>WEIGHT (DRY)</b>	90 KG

OPTIONS
RCD/ELCB IP30 OR IP66
TWO OR FOUR WHEEL
EXTRA LARGE ROLL FRAMES
15 LITRE LONG RANGE TANK
LEADS MADE TO MEASURE

The warranty does not cover damage caused by misuse, neglect, accident, improper installation, unauthorised repairs or modifications, normal wear and tear, or use of non-approved fuels or oils. Consumable parts such as filters, fuses, and cosmetic wear are not covered.

The generator must be serviced at regular intervals as specified in the user manual. Proof of purchase and service records may be required. As the Australian distributor, Genelite reserves the right to repair or replace defective parts at its discretion.