



# Genette

## GC130

**Model** GC130  
**Speed** 1500 RPM  
**Phase/Voltage** 3, 415  
**Frequency** 50 Hz

**Stdby Power** 145kVA / 116 kW  
**Prime Output** 130kVA / 104 kW  
**Fuel Capacity** 226 Litres

**Length** 2.32m  
**Width** 0.9m  
**Height** 1.54m  
**Weight** 1308 kg

### Engine

**Manufacturer** Cummins Diesel  
**Engine Model** 6BTAA5.9G2  
**Type & Cylinder** 4 Stroke – V16  
**Induction** Turbocharged Air to Air After Cooled  
**Fuel Consumption**  
30 L @ 100%, 23L @ 75%, 16L @ 50% Load  
**Coolant Capacity** 10.4 L  
**Governor** Electronic  
**Cubic Capacity** 5.9 L  
**Oil Capacity** 16.4 L

### Options

**Outlets** Single or 3 Phase Options  
**PMG** Option

### Controls

**Controller** Remote Start with Analog Metering  
**Circuit Breaker** Four Pole MCB  
**Battery Isolator** Fitted adjacent battery

### Alternator

**Alternator Brand / Model** Stamford / UCi274E  
**Type** Brushless  
**Harmonic Distortion** Less than 5%  
**Protection Class** IP 23  
**Insulation Class** Class H

East Coast Head Office Ph. 1300 305 912  
Ph. +61 7 3277 8626 Fax. +61 7 3277 8627  
24 Perrin Place, Salisbury QLD 4107

West Coast Head Office Ph. 1300 305 912  
Ph. +61 8 6305 0145 Fax. +61 8 6305 0219  
2/6 Quantum Link, Wangara WA 6065

**CALL US**  
**1300 305 912**