

# GH10000E-LRT

## 11kVA HONDA

**11kVA**  
**HONDA**  
GH10000E-LRT



### ENGINE

<b>MANUFACTURER</b>	Honda
<b>ENGINE MODEL</b>	GX630E
<b>TYPE &amp; CYLINDER</b>	O.H.V.
<b>STARTING</b>	Electric Start
<b>RUN TIME</b>	7hrs @ 60% load
<b>FUEL</b>	Unleaded Petrol
<b>CUBIC CAPACITY</b>	614 cm3
<b>HP 3000 RPM CONT</b>	11.9HP
<b>OIL CAPACITY</b>	1.8L

### TECHNICAL

<b>MODEL</b>	GH10000E-LRT
<b>TYPE</b>	Portable
<b>FREQUENCY</b>	50Hz
<b>PHASE/VOLTAGE</b>	1/240

SPEED	POWER		NOISE LEVEL	FUEL CAPACITY	CONTINUOUS OUTPUT
	Max Power		dBA @7m see *1		
	kW	kVA	dBA		
3000RPM	9	11	74	25L	11kVA

### ADDITIONAL INFO

<b>OUTLETS</b>	2 x 15 amp 240V outlets switched with thermal overload
<b>FRAME</b>	Extra large roll frame

### ALTERNATOR

<b>ALTERNATOR BRAND</b>	Mecc Alte
<b>TYPE</b>	Brushless
<b>HARMONIC DISTORTION</b>	Less than 5%
<b>INSULATION CLASS</b>	Class H

### DIMENSIONS

<b>LENGTH</b>	87cm
<b>WIDTH</b>	70cm
<b>HEIGHT</b>	60cm
<b>WEIGHT</b>	125kg

### OPTIONS

- RCD/ELCB IP30 OR IP66 outlets
- 4 wheel kit
- Fuel Tank Base with Roll Over Frame
- Oversized, Single or 3 phase alternators