



# Genelite

## GH14,000E-FBT



**PORTABLE POWER**

### Technical

<b>Model</b>	GH 14,000E-FBT
<b>Type</b>	Portable
<b>Speed</b>	3000 RPM
<b>Phase/Voltage</b>	1/240
<b>Frequency</b>	50 Hz
<b>Max Output @ 0.8pf</b>	11.6 kVA
<b>Noise Level (dBA @ 7m) Frame</b>	74
	Skid Base with Roll Over Frame

### Engine

<b>Manufacturer</b>	Honda
<b>Engine Model</b>	GX630
<b>Type</b>	O.H.V.
<b>Starting</b>	Electric start
<b>Fuel</b>	Unleaded Petrol
<b>Run Time</b>	11 hrs @60%
<b>Tank Capacity</b>	50 L
<b>HP 3000 rpm cont</b>	14.1 HP
<b>Cubic Capacity</b>	688 Cm3
<b>Oil Capacity</b>	1.9 L

### Alternator

<b>Alternator Brand</b>	Meccalte
<b>Type</b>	Brushless
<b>Harmonic Distortion</b>	Less than 5%
<b>Protection Class</b>	IP 23
<b>Insulation Class</b>	Class H

### Outlets

<b>Outlet</b>	2 x 15amp switched with thermal overload
---------------	--

### Dimensions & Weight

<b>Length</b>	105 cm
<b>Width</b>	55 cm
<b>Height</b>	70 cm
<b>Weight</b>	150 kg

### Options

<b>Outlets</b>	Weather protected IP33 & Weatherproof IP66
<b>Protection</b>	RCD/ELCB IP30 or IP66
<b>Wheel kits</b>	Four Wheel
<b>Alternators</b>	Oversized, Single or Three Phase

**POWERED by**  
**HONDA**™

**mecc alte spa**