


HY2000Si - 2KVA Hyundai









A. GENERAL FEATURES

MODEL H	Y2000Si	KVA	Max kVA 2.0 @0.8pf
---------------------------	---------	-----------------------	--------------------

DESCRIPTION

The Hyundai HY2000Si Petrol Inverter Generator is a simple to use source of portable power. With a massive 2000w / 2kW output and a low noise level of only 58dB you're assured of a clean, quiet, reliable source of power whether you're in a caravan, camping or a motor home. The HY2000Si comes with 2 standard 3 Pin sockets that will take any Australian 3 pin plug and also a 12V output for charging car or leisure batteries.

With the user in mind the lightweight, compact design incorporates a large carry handle and the tough exterior will protect against knocks and bangs, no matter what adventure you are on. The small footprint of this suitcase generator also makes it easy to store and simple to transport.

Like all Hyundai generators, the HY2000Si produces a pure sinewave output, so not only will it power your fridge or lighting but can handle much more sensitive equipment, such as TVs, laptop computers, tablets and smartphones.

B. GENERAL RATING

VOLTAGE		POWER		NOISE LEVEL	RUN START TIME	START
		Max Output @ 0.8pf		dBA @7m see *1		
		kw	kva	dBA	@75% Load	Recoil
2	240	1.6k/w	2.0kVA	58	4 Hours	Recoil

^{*1} At 1/4 Load at 7m from control panel side

,,,,,,,,,,,,,,,,,,,



HY2000Si - 2KVA Hyundai



C. TECHNICAL FEATURES

TECHNICAL		FEATURES
• POWER OUTPUT KW/KVA	2000 watt Continuous / 2200 Watt Maximum / Max Kva 2.5 @0.8pf	 LCD Display Control Panel
ENGINE DISPLACEMENT	80cc	• Outlets: 1 x 15 Amp 240V
• ENGINE MAKE	Hyundai	
ENGINE TYPE	IC80 - OHV, Single Cylinder	
• FUEL TANK CAPACITY	3.8 Litres	
• FUEL TYPE	4 - Stroke	

COMES WITH	DIMENSIONS	
• 12v Charging Cables	• Length: 500 mm	
Oil Filling Bottle	• Width: 270 mm	
Spark Plug Spanner	• Height: 450 mm	
Screwdriver	• Weight: 21 kg	

PH: 1300 305 912

Instruction Manual

D. CONTROL PANEL

LCD Display on Control Panel

